

| SDA-6 HDMI-I2S |  |              |         |           |               |         |
|----------------|--|--------------|---------|-----------|---------------|---------|
| DIP开关          | Describe (功能描述)  | Default (默认) | PSAUDIO | HOLOAUDIO | GUSTARD (歌诗德) | L. K. S |
| SW1            | DSD_ON OUTPUT FOR PIN13 (DSD ON使能引脚PIN13输入)  | OFF          | OFF     | OFF       | OFF           | OFF     |
| SW2            | DSD_ON OUTPUT FOR PIN14 (DSD ON使能引脚PIN14输入)  | OFF          | OFF     | OFF       | OFF           | ON      |
| SW3            | DSD_ON OUTPUT FOR PIN15 (DSD ON使能引脚PIN15输入)  | OFF          | OFF     | OFF       | ON            | OFF     |
| SW4            | DSD_ON OUTPUT FOR PIN16 (DSD ON使能引脚PIN16输入)  | OFF          | OFF     | OFF       | OFF           | OFF     |
| SW5            | PCM/DSD automatic detection (PCM/DSD自动检测)  | OFF          | OFF     | OFF       | ON            | ON      |
| SW6            | LRCLK and DATA SIGNAL opposition (LRCLK和DATA信号反相)  | OFF          | OFF     | OFF       | ON            | ON      |
| SW7            | DSD LR CHANNEL opposition (DSD左右声道互换)  | OFF          | ON      | OFF       | OFF           | ON      |
| SW8            | 1.PLL enable only used for AES and SPDIF, Optical (PLL开关, 只作用于AES和同轴, 光纤输入时)<br>2. In USB mode, when using external clock input, the input impedance can be set by this code. When ON, the input impedance is 50 ohms; when OFF, the input impedance is 75 ohms. (USB模式下, 使用外置时钟输入时, 可以通过该拨码设置输入阻抗。ON的时候, 输入阻抗为50欧; OFF的时候, 输入阻抗为75欧。) | ON           | /       | /         | /             | /       |
|                |  |              |         |           |               |         |